_ ECE 3600 Homework 6

Electromagnetics Due: Mon, 1/27/25

1. Textbook problem 1-7 (p49)

Name

A two-legged core is shown in below. The winding on the left leg of the core (N_1) has 600 turns, and the winding on the right (N_2) has 200 turns. The coils are wound in the directions shown in the figure. If the dimensions are as shown, then what flux would be produced by currents $i_1 = 0.5$ A and $i_2 = 1.00$ A? Assume $\mu_r = 1000$ and constant.



core depth = 15 cm

2. Textbook Example 1-2 (p20) with:

Mean magnetic length: $1_c := 50 \cdot cm$ Air gap length: $1_a := 0.06 \cdot cm$ Core cross-sectional area: $A_c := 16 \cdot cm^2$ Relative permeability of core: $\mu_r := 4000$ Effective air-gap cross-sectional area is 5% more than the core.

- a) Find the total reluctance of the core with the air gap. \mathcal{R}_{uq} = ?
- b) Find the required current so that the flux density of in the air gap is: $B_a := 0.5 \cdot \text{tesla}$ I = ?

